

## 4-Port USB KVM Switch

### For Control of 4 Servers/PCs

- VGA/SVGA Monitor Support
- USB Connection to Keyboard & Mouse
- Connects Up to 4 Servers/PCs
- PC/Server Selection Through Push Button or Hot Key Command
- Automatic Scanning of PCs Every 10 Seconds

#### FEATURES

- **4 KVM Ports**
- **Allows Control of 4 USB Style PCs From Single Keyboard, Mouse & Monitor**
- **Supports VGA, SVGA & Multisync monitors**
- **Supports Video Resolution 2048 x 1536 (Bandwidth Up to 400MHz)**
- **Supports USB Keyboard & Mouse**
- **Keyboard & Mouse Emulation for Error-Free Boot-Up**
- **Supports Microsoft IntelliMouse & Microsoft IntelliMouse Explorer**
- **PC Selection Via Push Button or Hot Keys**
- **Audible Feedback When Switching**
- **Auto Scan Mode**
- **LED Indicator for Each PC**
- **Auto Recall of CAPS LOCK, NUM LOCK & SCROLL LOCK Status for Each PC**
- **No Driver Required**
- **Bus Power, No AC Power Adapter Required**

**T**he D-Link DKVM-4U KVM switch is a handy device that allows you to control up to 4 PCs using only one monitor, keyboard and mouse. The monitor and the two input devices are connected directly to this KVM switch and not to the client computers. For office users with a need for several PCs, this KVM switch box eliminates the need for several monitors, keyboards and mice, saving the money and desktop space. The DKVM-4U is also a cost-effective solution for control of several servers in a computer room, allowing an engineer to handily manipulate all connected computers from a single monitor, keyboard and mouse.

*Save Money and Space.* The DKVM-4U allows you to control up to 4 computers from a single keyboard, monitor and mouse, so you don't have to purchase a monitor, keyboard and mouse for each PC. Your desktop will also look less chaotic. Your KVM switch can be placed underneath your desk, with 4 sets of KVM cables connecting from this switch box to 4 computers. Each KVM cable set includes a video cable for PC's VGA connector, and a single USB 2.0 cable for the PC's USB port. From the KVM switch box, you can connect to 2 USB devices: a USB keyboard and a USB mouse. 2 sets of KVM cables are provided for ready connection to 2 computers, the remaining KVM cables are optional.

*Easy Control.* You can switch quickly between the individual client computers by pushing a button on the DKVM-4U or by pressing the hot keys on your keyboard. The KVM switch confirms the switchover with an acoustic signal, and has LEDs indicating which PC is currently being served by the console. All connected PCs are automatically scanned every 10 seconds, so your monitor, keyboard and mouse are updated whenever you switch to a selected PC. CAPS LOCK, NUM LOCK and SCROLL LOCK key's status for each computer is automatically recalled. The DKVM-4U guarantees that the client PC does not crash when it is disconnected from KVM switch box.

*High Monitor Resolution Support.* The DKVM-4U is capable of supporting the most demanding resolutions (VGA, SVGA and Multisync monitors) of up to 2048 x 1536 at 75Hz refresh rate (bandwidth up to 400MHz) without any noticeable degradation in image quality.



## Technical Specifications

### Connectors to Computers

- 4 DB-15 HDDDB video connectors (to Computers' monitor ports)
- 4 USB 2.0 Type B connectors (to computers' USB ports)

### Connectors to Console

- DB-15 HDDDB video connector (to console monitor)
- USB Type A connector (to console USB keyboard)
- USB Type A connector (to console USB mouse)

### Computer Selection

- (Manually switching back and forth among 4 computers)
- Through push button
- Through hot keys
- Switching confirmation: buzzer sound

### Hot Key Menu Functions

- Scroll Lock + Scroll Lock + 1: switch to computer 1
- Scroll Lock + Scroll Lock + 2: switch to computer 2
- Scroll Lock + Scroll Lock + 3: switch to computer 3
- Scroll Lock + Scroll Lock + 4: switch to computer 4
- Scroll Lock + Scroll Lock + -->: switch to next computer
- Scroll Lock + Scroll Lock + <--: switch to previous computer
- Scroll Lock + Scroll Lock + B: beeper ON/OFF
- Scroll Lock + Scroll Lock + M: resets mouse and keyboard
- Scroll Lock + Scroll Lock + S: auto-scan mode every 10 seconds

### Diagnostic LEDs

4 port LEDs for 4 connected computers

## Physical & Environmental

### Power Consumption

5V 70mA

### Power Supply

Directly from connected computer's USB port, no external power adapter required

### Dimensions

178 (L) x 105(W) x 30.5(H) mm

### Weight

275 grams

### Emission (EMI)

- FCC Class B
- CE
- C-Tick

### O.S. Support

- Microsoft Windows 98SE, ME, NT, 2000, XP, NT 2003
- Linux Red Hat

### Box Includes

- DKVM-4U switch
- 2 sets of 1.8 m KVM cables (each includes 1 video cable, 1 USB 2.0 cable)
- Quick Installation Guide

### Optional KVM Cables

(Each includes 1 video cable, 1 USB 2.0 cable)

- DKVM-CU 1.8 m (6 ft)
- DKVM-CU3 3 m (10 ft)
- DKVM-CU5 4.5 m (15 ft)



## D-Link Worldwide Offices

<b>U.S.A.</b>	TEL: 1-800-326-1688	FAX: 1-866-743-4905	<b>Luxemburg</b>	TEL: 32-(0)2-517-7111	FAX: 32-(0)2-517-6500
<b>Canada</b>	TEL: 1-905-8295033	FAX: 1-905-8295223	<b>Poland</b>	TEL: 48-(0)-22-583-92-75	FAX: 48-(0)-22-583-92-76
<b>Europe (U. K.)</b>	TEL: 44-20-8731-5555	FAX: 44-20-8731-5511	<b>Hungary</b>	TEL: 36-(0)-1-461-30-00	FAX: 36-(0)-1-461-30-09
<b>Germany</b>	TEL: 49-6196-77990	FAX: 49-6196-7799300	<b>Singapore</b>	TEL: 65-6774-6233	FAX: 65-6774-6322
<b>France</b>	TEL: 33-1-30238688	FAX: 33-1-30238689	<b>Australia</b>	TEL: 61-2-8899-1800	FAX: 61-2-8899-1868
<b>Netherlands</b>	TEL: 31-10-282-1445	FAX: 31-10-282-1331	<b>India</b>	TEL: 91-022-26526696	FAX: 91-022-26528914
<b>Belgium</b>	TEL: 32(0)2-517-7111	FAX: 32(0)2-517-6500	<b>Middle East (Dubai)</b>	TEL: 971-4-3916480	FAX: 971-4-3908881
<b>Italy</b>	TEL: 39-02-2900-0676	FAX: 39-02-2900-1723	<b>Turkey</b>	TEL: 90-212-289-56-59	FAX: 90-212-289-76-06
<b>Sweden</b>	TEL: 46-(0)8564-61900	FAX: 46-(0)8564-61901	<b>Egypt</b>	TEL: 202-414-4295	FAX: 202-415-6704
<b>Denmark</b>	TEL: 45-43-969040	FAX: 45-43-424347	<b>Israel</b>	TEL: 972-9-9715700	FAX: 972-9-9715601
<b>Norway</b>	TEL: 47-99-300-100	FAX: 47-22-309580	<b>LatinAmerica</b>	TEL: 56-2-232-3185	FAX: 56-2-232-0923
<b>Finland</b>	TEL: 358-9-2707 5080	FAX: 358-9-2707-5081	<b>Brazil</b>	TEL: 55-11-218-59300	FAX: 55-11-218-59322
<b>Spain</b>	TEL: 34-93-4090770	FAX: 34-93-4910795	<b>South Africa</b>	TEL: 27-12-665-2165	FAX: 27-12-665-2186
<b>Portugal</b>	TEL: 351-21-8688493		<b>Russia</b>	TEL: 7-095-744-0099	FAX: 7-095-744-0099 #350
<b>Czech Republic</b>	TEL: 420-(603)-276-589		<b>China</b>	TEL: 86-10-58635800	FAX: 86-10-58635799
<b>Switzerland</b>	TEL: 41-(0)-1-832-11-00	FAX: 41(0)-1-832-11-01	<b>Taiwan</b>	TEL: 886-2-6600-0123	FAX: 886-2-6600-1188
<b>Greece</b>	TEL: 30-210-9914 512	FAX: 30-210-9916902	<b>Headquarters</b>	TEL: 886-2-6600-0123	FAX: 886-2-6600-9898